

# Pre-amplifier

## DK-1211

### Features:

- ◆ 10 inputs (5 microphone, 3 lines, 2 emergency), 4 outputs
- ◆ Independent volume control for each channel
- ◆ Treble and bass volume control
- ◆ Auto default (0 – 30 dB)
- ◆ No volume control for emergency input

### Technical Specification

MODEL	DK-1211
LINE input(AUX)	AUX1-AUX3 : 10K ohms( $\Omega$ ) 330mV, unbalanced
MIC input	MIC1-MIC5 : 600 ohms( $\Omega$ ) 5mV-12mV, unbalanced
EMC1 input	EMC1、EMC2 : 10K ohms( $\Omega$ ) 200mV, unbalanced
Priority level	Remote paging mic1>EMC>MIC2、MIC3、MIC4、MIC5、AUX1、AUX2、AUX3
LINE output	775mV
Freq. response	60Hz ~ 15k Hz ( $\pm$ 3dB)
Nonlinear Distortion	< 0.1% at 1k Hz
Signal to Noise ratio	> 70dB
Function Key	8 volume controls; 1 treble, 1 bass adjustment control 1 power switch
Indicator	POWER
Protection	AC FUSE X 0.5A X 1
Power supply cable	( $3 \times 0.75 \text{ mm}^2$ ) $\times$ 1.5M ( standard )
Power supply	AC 230V $\pm$ 10% 50 -60Hz
Power consumption	10~15W
Dimensions	89(H) $\times$ 483(W) $\times$ 366(D) mm
Net Weight	5.9Kg



### Connection Schematic



# 10-channel Monitor Panel

## DK-1212

### Features:

- ◆ 10 monitoring channels
- ◆ Built-in monitoring speaker
- ◆ Adjustable monitoring volume
- ◆ LED indicators for levels

### Technical Specification

MODEL	DK-1212
Built-in Speaker B Power	5W
Line IN	70V/100V (output audio signal from amplifiers)
Frequency Response	100 Hz~16 kHz $\pm$ 3.5dB
Total harmonic distortion(THD)	<0.5at 1/3 Rated power
Signal to Noise Ratio S/N	>70 dB 1.5 mV
Monitored channel number	10 (CH1-CH10)
Monitoring speaker	Built-in high-fidelity (HiFi) 5W full frequency speaker
Function Key	1 power switch, a selector knob (0-10), a monitoring volume control
Indicator	POWER ON, LEVEL 2, 4, 6, 8 and 10
Protection	AC FUSE X 0.5A X 1
Power cord	( $3 \times 0.75 \text{ mm}^2$ ) $\times$ 1.5M ( standard )
Power supply	AC 230V $\pm$ 10% 50 -60Hz
Power consumption	10~15W
Dimensions	89(H) $\times$ 483(W) $\times$ 366(D) mm
Net Weight	6.3Kg



### Connection Schematic

